



iTraceRT-MVT-300/TLN-1











Reliable INS / GNSS solutions for most demanding automotive environments

iTraceRT-MVT is a member of iMAR's iNAT series and one of the smallest yet powerful MEMS based INS/GNSS inertial navigation, measurement, surveying and control systems. It provides real time kinematic measurements, such as acceleration, angular rate, attitude, true heading, velocity and position with a data update rate of up to 1'000 Hz. iTraceRT-MVT is the successor of iMAR's well-known iTraceRT-Fxx and comes with advanced integrated sensor and data fusion technology.













APPLICATIONS

Automotive & Transportation Unmanned & Manned Stabilization & Control Localization & Navigation

KEY FEATURES

MIL-STD qualified Inertial Data Logging (128 GByte) Single & Dual Antenna GNSS Minimum Latency & Jitter

PERFORMANCE


Data Rate up to1'000 Hz
Heading < 0.07 °
Attitude < 0.02 °
Position < 0.01 m






iTraceRT-MVT-300 - Family

ONE ARCHITECTURE FOR ALL TECHNOLOGIES -





MADE FOR YOUR APPLICATION



Easy to use: iXCOM-CMD GUI / HMI incl. powerful wizard. iTraceRT-MVT architecture allows application specification software configurations in order to achieve best performance even in most demanding environments. Integrated maintenance-free realtime clock.



INTERFACES & PROTOCOLS

NMEA, IENA, RTCM 104, TCP/IP, UDP, EtherCat, NTRIP, NTP Time Server, CAN, Ethernet, UART RS422/RS232, GP-I/O, PPS, PPT, ODO, USB; iXCOM communication protocol for all processed and raw data.



QUALIFICATION

iTraceRT-MVT is qualified according to MIL-STD-810H, MIL-STD-461G, MIL-STD-704F and partially DO160G,CE, partially EN 50121.



EXTENSIVE AIDING CAPABILITIES

iTraceRT-MVT is designed to operate with additional external sensors, e.g. odometer, LiDAR, pitot-sensors, magnetometer, balise etc.



DATA FUSION

The integrated advanced 42+ state extended Kalman filter allows advanced and predictable data fusion of multiple data sources, e.g. INS, GNSS and additional sensors.



MODULARITY

The modular nature of iNAT-Family allows iMAR to configure the systems with a wide range of best in class inertial sensors and GNSS receivers, expandable at any time and best fitted to customer's needs.





iTraceRT-MVT-300/TLN-1

TECHNICAL DATA

■ NAVIGATION PERFORMANCE

Position & Velocity Accuracy

| Position (GNSS RTK post-proc.) **) | ± 0.01 m |
|--|-----------|
| Position (GNSS RTK) **) | ± 0.02 m |
| Position (GNSS with / w/o SBAS) \pm 0.6 m | / ± 1.2 m |
| Position (GNSS denied + odometer) \dots 0.2 % of dist. | travelled |
| Position (GNSS denied w/o odometer *) **) | 0.3 % DT |
| Velocity (RTK) | 0.01 m/s |
| Side slip angle (accuracy given for $v > 10 \text{ m/s}$) | 0.1 ° |

Angles

| Range (Heading/Yaw, Roll, Pitch) unlimited |
|--|
| Heading/Yaw **) |
| Heading/Yaw (after 60 s GNSS denied) |
| Heading/Yaw (post-proc.) **) 0.02 ° |
| Roll/Pitch **) |
| Roll/Pitch (initial, w/o any aiding) |
| Dual-Antenna initial Heading, with 1 m baseline 0.2 $^{\circ}$ |
| with 2 m baseline 0.1 ° |

■ MECHANICAL

| Size (W x H x D) | approx. 102 x 65 x 122 mm |
|------------------|-------------------------------|
| Weight | approx. 780 g |
| Connectors M | MIL-C-38999 III (Data, Power) |
| | SMA (Antenna) |
| | M12 (Ethernet) |

■ GNSS

| Constellations | . GPS, GAL, GLO, BDS, IRNSS |
|--------------------------------|--------------------------------|
| Frequencies | up to all frequencies |
| Features SBA | S, RTK, PPP, Basestation, etc. |
| High speed version (> 515 m/s) | on request |

■ ELECTRICAL

| Operating voltage9 - 34 V DC |
|----------------------------------|
| Power consumption approx. 10.5 W |
| Power inputs |

■ IMU SPECIFICATION

| ACCELEROMETER | GYROSCOPE |
|--|-----------------|
| Range \pm 10 g . | ± 400 °/s |
| Resolution < 2 μg . | <0.0001 °/s |
| Bias instability (AV) < 50 μg . | 0.5 °/h |
| Initial Bias $\dots < 2 \text{ mg}$. | < 0.07 °/s |
| Bias filtered $\dots < 0.5 \text{ mg}$. | \dots < 2 °/h |
| Noise (AV) 45 μ g/ \sqrt{Hz} . | 0.15 °/√h |
| Non-orthonality \dots < 0.3 mrad . | < 0.3 mrad |
| Scale factor error 500 ppm . | 500 ppm |
| Non-linearity | 50 ppm |
| Bandwidth 240 Hz . | 240 Hz |

■ DATA OUTPUT, DATA INPUT

Data Output

| Data Rate |
|---|
| Latency / Jitter / Time stamp < 6 ms / < 1 ms / < 1 μ |

Input / Output Interfaces

PPS, PPT, GP Trigger/Sync I/O, odometer / VMS input (wide range opto-coupler; RS422 level)

Communication Interfaces (options)

Ethernet (TCP/IP, UDP), $4 \times$ UART (RS232/422), $2 \times$ CAN, USB, NMEA183, ARINC 825, NTRIP caster with RTCM 104, NTP, iXCOM, ROS-2, Python, SDK C++

■ ENVIRONMENTAL

| Temperature (operational / storage)40 +71 °C / -55 +85 °C |
|---|
| Shock (operational) 60 g, 11 ms (half-sine) |
| Shock (endurance) 1'000 g, 0.5 ms (half-sine) |
| Vibration operational 10 - 2'000 Hz, 10 g RMS |
| Vibration endurance 10 - 2'000 Hz, 20 g RMS |
| Maximum altitude 60'000 ft |
| Environmental protection |
| Magnetic sensitivity none |
| Fully hermetic sealed (resistant against Helium) on request |
| MTBF49'000 h |

^{*)} for road and rail applications **) after sufficient availability of GNSS aiding and motion dynamics

Each individual **iTraceRT-MVT-300** undergoes a calibration and verification testing process at iMAR's calibration laboratory. Performance specifications are based on comprehensive field testing and results from real-world applications, and are regularly tested to ensure continued conformance to such specifications.







iTraceRT-MVT-300 - Family

SYSTEM FEATURES AND SENSOR PERFORMANCES-

| iTraceRT- | PERFOR | RMANCE | GYROSCOPE | | | ACCELEROMETER | | | COST | |
|-----------|----------|--|-------------|-----------------|-----------------------------|------------------------------|---------------------------|-----------------------|----------------|-------|
| MVT-300 | Accuracy | Vibration immunity | [°/s] Range | [°/√h] ARW (AV) | AV [°/h] Bias instability | [%] Scale factor error | [g] | [mg] Bias day-to-day | [μg√Hz] VRW | |
| TLN-2 | **** | **** | ±400 1) | <0.15 | <0.3 | <0.05 | ±10 ¹⁾ | ±1 | <25 | €€€€€ |
| TLN-1 | **** | **** | ±400 | <0.15 | <0.3 | <0.05 | ±10 ¹⁾ | ±2 | <45 | €€€€€ |
| TLE-ULN1 | *** | *** | ±200 | <0.03 | <0.8 | <0.2 | ±10 ¹⁾ | ±2 | <60 | €€€€€ |
| TLE-LN1 | **** | *** | ±450 | <0.06 | <0.8 | <0.2 | ±10 ¹⁾ | ±2 | <60 | €€€€€ |
| TLE-SP1 | *** | *** | ±450 | <0.08 | <1.2 | <0.2 | ±10 ¹⁾ | ±2 | <60 | €€€€€ |
| TLD | *** | *** | ±500 ¹) | <0.15 | <2.5 | <0.3 | ±8 ¹) | ±2 | <23 | €€€€€ |
| Custom | | Option: integration of any inertial and GNSS sensors | | | | | | | | |
| | | Table Notes: all values1o, except ranges | | | | | 1) other ranges available | | | |









General information about iMAR's INS/GNSS solutions for all applications









iTraceRT Family







